



- Article features
- Transformer core can be easily divided
  - excellent for retrofitting, as the primary circuit does not have to be interrupted
  - simple and secure attachment to busbar - audible latching of current transformer
  - well fixable by some clamping screws

| Technical data             |                                                        |
|----------------------------|--------------------------------------------------------|
| Round conductor            | ∅ 40 mm                                                |
| Primary rail               | 30 x 15 mm, 50 x 12 mm, 2 x 50 x 10 mm, 3 x 40 x 10 mm |
| Dimensions (W x H x D)     | 120 x 123 x 43 mm                                      |
| Instrument security factor | FS 5                                                   |

### Variants (50)

| Article no. | Description             |
|-------------|-------------------------|
| 70030-3083  | IAP 500/1A 10VA Kl. 1   |
| 70030-3084  | IAP 600/1A 15VA Kl. 1   |
| 70030-3085  | IAP 750/1A 20VA Kl. 1   |
| 70030-3086  | IAP 800/1A 30VA Kl. 1   |
| 70030-3087  | IAP 1000/1A 45VA Kl. 1  |
| 70030-3088  | IAP 100/1A 2.5VA Kl. 3  |
| 70030-3089  | IAP 125/1A 3.75VA Kl. 3 |
| 70030-3090  | IAP 150/1A 3.75VA Kl. 3 |
| 70030-3091  | IAP 200/1A 3.75VA Kl. 3 |
| 70030-3092  | IAP 250/1A 7.5VA Kl. 3  |
| 70030-3093  | IAP 300/1A 10VA Kl. 3   |
| 70030-3100  | IAP 500/5A 10VA Kl. 1   |
| 70030-3101  | IAP 600/5A 15VA Kl. 1   |
| 70030-3102  | IAP 750/5A 20VA Kl. 1   |
| 70030-3103  | IAP 800/5A 30VA Kl. 1   |
| 70030-3104  | IAP 1000/5A 45VA Kl. 1  |

| Article no. | Description              |
|-------------|--------------------------|
| 70030-3105  | IAP 100/5A 2.5VA Kl. 3   |
| 70030-3106  | IAP 125/5A 3.75VA Kl. 3  |
| 70030-3107  | IAP 150/5A 3.75VA Kl. 3  |
| 70030-3108  | IAP 200/5A 3.75VA Kl. 3  |
| 70030-3109  | IAP 250/5A 7.5VA Kl. 3   |
| 70030-3110  | IAP 300/5A 10VA Kl. 3    |
| 70097-1885  | IAP 100/1A 1.25VA Kl. 1  |
| 70097-1886  | IAP 100/5A 1.25VA Kl. 1  |
| 70097-1887  | IAP 1000/5A 10VA Kl. 0.5 |
| 70097-1888  | IAP 125/1A 1.25VA Kl. 1  |
| 70097-1889  | IAP 150/5A 2.5VA Kl. 1   |
| 70097-1890  | IAP 200/1A 3.75VA Kl. 1  |
| 70097-1891  | IAP 200/5A 3.75VA Kl. 1  |
| 70097-1892  | IAP 250/5A 3.75VA Kl. 1  |
| 70097-1893  | IAP 300/1A 5VA Kl. 1     |
| 70097-1894  | IAP 300/5A 5VA Kl. 1     |
| 70097-1895  | IAP 400/5A 7.5VA Kl. 1   |
| 70097-1896  | IAP 500/5A 5VA Kl. 0.5   |
| 70097-1897  | IAP 60/5A 1.25VA Kl. 3   |
| 70097-1898  | IAP 600/5A 10VA Kl. 0.5  |
| 70097-1899  | IAP 750/5A 10VA Kl. 0.5  |
| 70097-1900  | IAP 800/1A 10VA Kl. 0.5  |
| 70097-1901  | IAP 800/5A 10VA Kl. 0.5  |
| 70097-3064  | IAP 60/1A 1.25VA Kl. 3   |
| 70097-3139  | IAP 500/1A 5VA Kl. 0.5   |
| 70097-3245  | IAP 400/1A 7.5VA Kl. 1   |
| 70097-3272  | IAP 75/5A 1.25VA Kl. 3   |
| 70097-3273  | IAP 75/1A 1.25VA Kl. 3   |
| 70097-3274  | IAP 150/1A 2.5VA Kl. 1   |
| 70097-3275  | IAP 250/1A 3.75VA Kl. 1  |
| 70097-3276  | IAP 600/1A 10VA Kl. 0.5  |
| 70097-3277  | IAP 750/1A 10VA Kl. 0.5  |
| 70097-3279  | IAP 1000/1A 10VA Kl. 0.5 |
| 70097-3444  | IAP 125/5A 1.25VA Kl. 1  |